


## B<sup>1</sup> Electronics box and B<sup>1</sup> two-gang junction box



### B<sup>1</sup> electronics box

- with separator wall for separating electrical circuits
- with 4 screw domes
- Suitable for all types of formwork
- 2-piece with moulded rear part
- Two slots for B<sup>1</sup> Prefix® system wings
- Rear part of box with slot for support element
- Standardised combination distance 71 mm

<b>Article no:</b>	<b>1268-01</b>
EAN:	4013456550544
Length	160 mm
Width	75 mm
Depth	91 mm
Installation opening Ø	60 mm
Break-out openings for DIN EN Ø 20/25 mm conduits	7
Break-out openings for DIN EN Ø 32/40 mm conduits	2
Markings for cables up to Ø 16 mm	7
Number of parts	9
Packaging inner/dispatch	5/50

The B<sup>1</sup> electronics box and B<sup>1</sup> two-gang junction box are especially suitable for installations in on-site mixed concrete vertical formwork. The B<sup>1</sup> electronics box provides plenty of space for accessory installations, and additional space for devices such as switch actuators or other components for smart home applications. The relevant separator wall allows the standardised installation of bus and operating voltages in a single box. B<sup>1</sup> Two-gang junction boxes allow the installation of block and pre-wired accessories, and provide space for the assembly of cable for multimedia connections.

- Plenty of space for accessories and cables
- Separator wall for the standardised incorporation of two voltage types
- Flat front part for fast, easy nailing
- Innovative conduit entries for fast processing on the construction site
- Slot for B<sup>1</sup> Prefix® system wing set
- Spring travel ensures secure fit in standing formwork

