

Compact PD and Multi-PD distribution box



Flat Box, 4x3p black (connected 2+2) + connection wires WAGO

- Connection via prefabricated 2.5 mm² core cable
- Suitable for mounting in suspended ceilings and underfloor areas
- Suitable M20 cable gland for a 3x1.5 mm² or 3x2.5 mm² feed line: AGRO Progress 1571.20.110
- Suitable cable M20 cable gland for two feed lines 3x1.5 mm²: AGRO Progress 1571.20.2.075

Article no:	AT3215
EAN:	8712259328034
Length	120 mm
Width	120 mm
Depth	40 mm
Poles Connection	2 x 3 pole
Outlet connector L1	2x 3pole, black
Outlet connector L2	2x 3pole, black
Pre-wiring	2,5 mm ²
Rated voltage	400 V
Protection class	IP20
Cover model	Blind cover
Operation temperature	- 40°C / + 70°C
Cover attachment	Snap on
Colour	light grey
Halogen-free	Yes
Dispatch	10

The compact PD distribution boxes for connector systems really show off their advantages especially well in electrical installations in confined spaces, such as in raised floors, underfloor systems or suspended ceilings. Thanks to their compact design and low overall height, they cut a slim figure even where space is limited. The prefabricated distribution boxes can be used as a transition from sheathed cables to the pluggable electrical installation or as a 100% pluggable box. Due to the factory pre-wiring, the error potential is practically zero, since only the components / connectors are connected at the installation site via a "click". Versions with 3-, 4- or 5-pole connectors are possible. The distribution boxes of the compact Multi-PD series can be mechanically connected to each other. This easy to lock system means that several boxes can be lined up next to each other so that larger distribution units can also be set up. Additional fixing lugs on the outside of the box offer a practical option for wall or ceiling attachment or fixing to the floor. For the compact PD and Multi-PD distribution boxes, prefabricated distribution boxes for up to 9 outlets as well as empty boxes are available, which can be equipped individually.